



## ARRANCADOR Y/A

LC3 e LE3-D12/17/25/40/50/63/80-P

POTÊNCIA		CONSUMO MÉDIO DE MOTORES TRIF. A 380V		FUSÍVEIS	REGULAÇÃO DO RELÉ R
Kw	Cv	A	A (*)	A	A
3	4	6,6	3,8	10	2,5 a 4
4	5,5	8,5	4,9	12	4 a 6
5,5	7,5	11,5	6,6	16	5,5 a 8
7,5	10	15,5	8,9	20	7 a 10
10	13,5	20	11,6	25	10 a 13
11	15	22	12,7	25	10 a 13
15	20	30	17,4	32	13 a 18
18,5	25	37	21,4	40	18 a 25
22	30	44	25,5	50	23 a 32
30	40	60	34,8	63	30 a 40
37	50	72,5	42	80	38 a 50
45	60	85	49,3	100	48 a 57
55	75	105	60,9	125	57 a 66
75	100	138	80	160	66 a 80

BOBINAS		
Tensão	Referência	Contactor
220 V	LX1-D09220	LC1-D 09 12
380 V	LX1-D09380	
220 V	LX1-D16220	LC1-D 16 25
380 V	LX1-D16380	
220 V	LX6-D40220	LC1-D 40-50 63-80
380 V	LX6-D40380	



Telemecanique

DES. 4082-M-1  
1-10-82